



IS-0736 REV02

## HORIZON II O5B / O5K PENDANT MOUNT FLUORESCENT & LED INSTALLATION INSTRUCTIONS

**NOTE:** The following instructions provide general guidelines for product installation.

For additional information, consult the applicable electrical codes or contact factory directly

for support before attempting anything with uncertainty.

**CAUTION**: Do not assemble fixture runs on floor.

**WARNING:** Risk of fire and electrical shock. DISCONNECT POWER AT ELECTRICAL PANEL before installing

or servicing this product.


## **GENERAL SAFETY INSTRUCTIONS:**

- 1. Read all instructions prior to installing this fixture.
- 2. Keep protective film/plastic on fixtures during installation to protect surface from damage or dirt.
- 3. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
- 4. All wiring must be performed by a qualified electrician in accordance with national and local building and electrical codes.
- 5. This fixture must be suitably grounded for your protection against shock hazards and to assure proper operation.
- 6. Make sure that the power source conforms to the requirements of this fixture.

HORIZON II O5B / O5K
PENDANT MOUNT
FLUORESCENT & LED
INSTALLATION INSTRUCTIONS



FIG. 1 shows an aircraft cable hanger assembly. The specific hanger type for your fixture(s) is identified on the Hanger Installation Instruction Sheet.



## **LEGEND**


- Fluorecent only
- LED only
- Fluorescent & LED

## STEP-BY-STEP INSTRUCTIONS

ETEP 1 Install HANGER
BRACKETS into ceiling at the required distances. Mounting distances are listed in Table A.
HANGER BRACKETS MUST BE INSTALLED IN A STRAIGHT LINE. (see FIG. 2)


DISTANCE BETWEEN MOUNTING CENTERS	
FIXTURE	DISTANCE
4' T8	49.3" / 1253mm
6' T8	74.4" / 1889mm
8' T8	98.4' / 2499mm
12'T8	147.4" / 3744mm
4' T5	34.8" / 885mm
6' T5	70.7" / 1795mm
8' T5	94.3" / 2395mm
12' T5	141.3" / 3589mm

Table A





- **11 STEP 2** Suspend start fixture using the supplied hanger system. [see Hanger Installation Instructions]
- **EXECUTE:** STEP 3 \*\*This step is only required for fixtures in a run configuration\*\* Suspend next fixture and mate it to the previous fixture [See FIG. 3A, 3B & 3C]



- **11 STEP 4** Repeat STEP 3 until run is complete.
- **F** STEP 5 Install all lamps.
- **STEP 6** Make all electrical connections and finalize hanger installation. [See Hanger Installation Instrctions]
- **STEP 7** Balance fixtures [see FIG. 4] and make final adjustments to height and straightness of fixtures. [See Hanger Installation Instructions]

